## RabbitCore® RCM3400

Microprocessor Core Module

The compact, analog-enabled RabbitCore RCM3400 is designed for embedded applications that require analog functionality.




## **Overview**

The RabbitCore RCM3400 core module, featuring the Rabbit® 3000 microprocessor, is designed for embedded control and monitoring applications requiring analog functionality. Its small size and ease of use when paired with Dynamic C® allow engineers to develop a control and monitoring solution for many of today's embedded applications. The Ethernet-ready RCM3400 comes pre-assigned with a MAC ID, along with a development board 10Base-T reference design. Built-in low EMI features, including a clock spectrum spreader, practically eliminate EMI problems, helping to pass CE and RF emissions tests.

Rabbit hardware and Dynamic C are designed in a complementary fashion for maximum performance and ease of use in embedded systems. The additional software components in Dynamic C allow you to add functionality for embedded application customization.

To evaluate and learn more about the RCM3400, please visit www.rabbit.com/products/rcm3400/.

## **Application Highlight**



**Potential Applications:** Device intelligence, embedded control, sensor reading, serial device coordinator, handheld remote devices, and GPS/AVL applications.

## **Features and Benefits**

- Rabbit 3000 microprocessor at 30 MHz
- Up to 512K Flash/512K SRAM
- 8 channel 12-bit A/D with programmable gain
- 47 digital I/O and 5 serial ports (IrDA, HDLC, asynch, SPI)
- MAC ID installed
- Compact size simplifies integration
- Ready-made platform for fast time-to-market, up to 3 months of design integration time savings
- · Low-cost embedded microprocessor module



	RCM3400 RabbitCore® Specifications	
Feature	RCM3400	RCM3410
Microprocessor	Low-EMI Rabbit® 3000 at 30 MHz	
Flash Memory	512K	512K
SRAM	512K	512K
Backup Battery	Connection for user-supplied backup battery (to support RTC and SRAM)	
Analog Inputs	8 channels single-ended or 4 channels differential Programmable gain 1, 2, 4, 5, 8, 10, 16, and 20 V/V	
A/D Converter Resolution	12 bits (11 bits single-ended)	
<ul> <li>A/D Conversion Time (including 120 μs raw count and Dynamic C)</li> </ul>	180 μs	
General-Purpose I/O	47 parallel digital I/0 lines:  • 41 configurable I/O  • 3 fixed inputs  • 3 fixed outputs	
Additional Inputs	Startup mode (2), reset in, CONVERT	
Additional Outputs	Status, reset out, VREF	
Auxiliary I/O Bus	Can be configured for 8 data lines and 6 address lines (shared with parallel I/O lines), plus I/O read/write	
Serial Ports	5 shared high-speed, CMOS-compatible ports: <ul> <li>All 5 configurable as asynchronous, 3 as clocked serial (SPI), and 2 as SDLC/HDLC</li> <li>1 asynchronous serial port dedicated for programming</li> <li>Support for MIR/SIR IrDA transceiver</li> </ul>	
Serial Rate	Maximum asynchronous baud rate = CLK/8	
Slave Interface	A slave port allows the RCM3400 to be used as an intelligent peripheral device slaved to a master processor, which may either be another Rabbit 3000 or any other type of processor	
Real-Time Clock	Yes	
Timers	Ten 8-bit timers (6 cascadable), one 10-bit timer with 2 match registers	
Watchdog/Supervisor	Yes	
Pulse-Width Modulators	10-bit free-running counter and four pulse-width registers	
Input Capture	2-channel input capture can be used to time input signals from various port pins	
Quadrature Decoder	2-channel quadrature decoder accepts inputs from external incremental encoder modules	
Power	3.0–3.45V DC @ 29.4 MHz, 2.8–3.45V DC @ 14.7 MHz 97 mA @ 3.3V, 29.4 MHz; 57 mA @ 3.0V, 14.7 MHz	
Operating Temperature	-40° C to +85° C	
Humidity	5% to 95%, non-condensing	
Connectors	Two 2 × 17, 1.27 mm pitch	
Board Size	1.160" × 1.375" × 0.31" (29.5 mm ×34.9 mm × 7.9 mm)	
	Pricing	
Price (qty. 1/100) Part Number	\$69/\$55 20-101-0561	\$59/\$49 20-101-0562
Development Kit Part Number	\$399 101-0587	None
	I	l .

