

Toroidal - Twin Primary Transformers

115V/230V ac

multicomp




A high quality range of open style toroidal transformers with flying leads. Featuring a dual 115V 50/60Hz primary winding for series (230V) or parallel (115V) connection only. Secondary windings can be connected in series or parallel or used independently.

Features:

- Very high quality construction.
- High efficiency and smaller size compared to conventional EI transformers.
- Extremely low radiated magnetic field, suitable for sensitive electronics.
- Double insulated primary leadouts.
- Flexible leadouts can be trimmed to any length without the need of removal of enamel.
- Design, manufactured and tested in accordance with EN60742, EN60065 and EN60950.
- 100% electrical and flash tested.
- Supplied with mounting dish, bolt and 2 foam pads.
- Pri/Sec leads 0°

Schematic TA Range General Purpose Toroidal Transformers



Primary

Dual primary winding for connection in series or parallel only

Input Voltage : 115 or 230V \pm 10% 50/60Hz.

DC resistance : 2 x 7.3 Ohms \pm 15% at 20°C

Magnetising current : 9.0mA approximate at 230V 50Hz (18mA approximate at 115v 50Hz)

Termination

Primary leads double insulated with PVC sleeving for a minimum of 2 0mm.

Lead lengths \pm 5mm approximate. All leads ends tinned to 6 mm.

multicomp

Toroidal - Twin Primary Transformers

115V/230V ac



Losses

Iron loss : 0.98 Watts approximate.
Copper loss : 11.4 Watts approximate.
Efficiency : 91.0% typical.
Temperature rise : 54°C approximate.
Ambient rated : 40°C.

Temperature Class

Winding wire : Class H (180°C)
Insulation system : Class B (130°C)
Leadout insulation : Class A (105°C)
Overall : Class A (105°C)

Supplied with

1 x 70mm dished mounting plate.
2 x 70mm neoprene mounting pads.
1 x M6 x 50mm screw, nut & washer.

Specifications

On Load Sec V	Rated amps per Sec	Off load Sec V	Sec Flex Gauge	Sec Ohms at 20°C	Part Number
12	5.00	13 .2	18 AWG	0.12	MCTA120/12
15	4.00	16.4	20 AWG	0.19	MCTA120/15
18	3 .33	19.6		0.29	MCTA120/18
25	2.40	27.3		0.55	MCTA120/25
55	1.09	59.5		2.18	MCTA120/55




Toroidal - Twin Primary Transformers

115V/230V ac



Schematic TI Range General Purpose Toroidal Transformers



Primary

Input Voltage: 230V \pm 10% 50/60Hz.

DC resistance: 6.3 Ohms \pm 15% at 20°C

Magnetising current: 14.5mA approximate 230V 50Hz.

Termination

Primary leads double insulated with PVC sleeving for a minimum of 20mm.

Lead lengths \pm 5mm approximate. All leads ends tinned to 6mm.

Losses

Iron loss : 1.49 Watts approximate.

Copper loss : 16.9 Watts approximate.

Efficiency : 92.0% typical.

Temperature rise : 56°C approximate.

Ambient rated : 40°C.

Temperature Class

Winding wire : Class H (180°C)

Insulation system : Class B (130°C)

Leadout insulation : Class A (105°C)

Overall : Class A (105°C)

Approximate dimensions/weight (mounting excluded)

Diameter : 110.0 mm*

Height : 51.0 mm*

Weight : 2.20 kg

* allow extra 5mm over leadout area

Supplied with

1 x 90mm dished mounting plate

2 x 90mm neoprene mounting pads

1 x M6 x 60mm screw, nut & washer



Toroidal - Twin Primary Transformers

115V/230V ac



Specification Table

VA	Regulation % typical	Temperature rise (°C)	Diameter	Height	Weight (Kg)	Fixing bolt
15	14	27	64.5	30.5	0.3	M5 x 40
30		42	73	31	0.5	
50	13	50	81	34.5	0.6	
60	12	47	91.5	39	0.8	M6 x 50
80	11	52	87.5		1.0	
100	10		91	46	1.1	
120	9	54	95	47	1.3	M6 x 60
160	8		105		1.6	
225	7	56	110	51	2.2	
250		55	119.5	53.5	2.4	
300	6	56	125	54	2.8	M8 x 75
500	5	53	136	59	4.3	
625		59	139	71	5.2	
800	4	60	163	59	6.3	M8 x 80
1000			167	70.5	7.5	

Dimensions : Millimetres

Maximum ambient temperature 40°C.

Overall temperature rating Class A (105°C).

Secondary voltage tolerance $\pm 1\%$ at nominal input and full resistive load.

All leads 150mm long, stripped and tinned for last 6.0mm.

Note: Under no circumstances should both ends of any fixing bolt be allowed to come simultaneously in contact with metal chassis or framework so that an electrical path is formed through the bolt in the centre of the transformer via the external framework. This would constitute a shorted turn and would cause irreparable damage.

Toroidal - Twin Primary Transformers

115V/230V ac



Part Numbers

Load (VA)	Specification	Part Number
15	0-6V, 0-6V @ 1.25A	MCTA015/06
	0-9V, 0-9V @ 0.83A	MCTA015/09
	0-12V, 0-12V @ 0.63A	MCTA015/12
	0-15V, 0-15V @ 0.5A	MCTA015/15
	0-18V, 0-18V @ 0.42A	MCTA015/18
30	0-6V, 0-6V @ 2.5A	MCTA030/06
	0-12V, 0-12V @ 1.25A	MCTA030/12
	0-15V, 0-15V @ 1A	MCTA030/15
	0-18V, 0-18V @ 0.83A	MCTA030/18
	0-25V, 0-25V @ 0.6A	MCTA030/25
50	0-6V, 0-6V @ 4.17A	MCTA050/06
	0-9V, 0-9V @ 2.78A	MCTA050/09
	0-12V, 0-12V @ 2.08A	MCTA050/12
	0-15V, 0-15V @ 1.67A	MCTA050/15
	0-18V, 0-18V @ 1.39A	MCTA050/18
	0-25V, 0-25V @ 1A	MCTA050/25
60	0-9V, 0-9V @ 3.33A	MCTA060/09
	0-15V, 0-15V @ 2A	MCTA060/15
	0-18V, 0-18V @ 1.67A	MCTA060/18
	0-25V, 0-25V @ 1.2A	MCTA060/25
100	0-12V, 0-12V @ 4.17A	MCTA100/12
	0-15V, 0-15V @ 3.33A	MCTA100/15
	0-18V, 0-18V @ 2.78A	MCTA100/18
	0-25V, 0-25V @ 2A	MCTA100/25
120	0-12V, 0-12V @ 5A	MCTA120/12
	0-15V, 0-15V @ 4A	MCTA120/15
	0-18V, 0-18V @ 3.33A	MCTA120/18
	0-25V, 0-25V @ 2.4A	MCTA120/25
	0-55V, 0-55V @ 1.09A	MCTA120/55
160	0-12V, 0-12V @ 6.67A	MCTA160/12
	0-15V, 0-15V @ 5.33A	MCTA160/15



Toroidal - Twin Primary Transformers

115V/230V ac



Part Numbers

Load (VA)	Specification	Part Number
160	0-18V, 0-18V @ 4.44A	MCTA160/18
	0-25V, 0-25V @ 3.2A	MCTA160/25
	0-30V, 0-30V @ 2.67A	MCTA160/30
	0-55V, 0-55V @ 1.45A	MCTA160/55
250	0-12V, 0-12V @ 10.42A	MCTA250/12
	0-18V, 0-18V @ 6.94A	MCTA250/18
	0-25V, 0-25V @ 5A	MCTA250/25
	0-30V, 0-30V @ 4.17A	MCTA250/30
	0-35V, 0-35V @ 3.57A	MCTA250/35
	0-40V, 0-40V @ 3.13A	MCTA250/40
	0-45V, 0-45V @ 2.78A	MCTA250/45
	0-50V, 0-50V @ 2.5A	MCTA250/50
300	0-25V, 0-25V @ 6A	MCTA300/25
	0-30V, 0-30V @ 5A	MCTA300/30
	0-35V, 0-35V @ 4.28A	MCTA300/35
	0-55V, 0-55V @ 2.73A	MCTA300/55
80	0-9V, 0-9V @ 4.44A	MCTA080/09
	0-12V, 0-12V @ 3.33A	MCTA080/12
	0-15V, 0-15V @ 2.67A	MCTA080/15
	0-18V, 0-18V @ 2.22A	MCTA080/18
	0-25V, 0-25V @ 1.6A	MCTA080/25
	0-55V, 0-55V @ 0.73A	MCTA080/55
225	0-12V, 0-12V @ 9.38A	MCTA225/12
	0-15V, 0-15V @ 7.5A	MCTA225/15
	0-18V, 0-18V @ 6.25A	MCTA225/18
	0-25V, 0-25V @ 4.5A	MCTA225/25
	0-30V, 0-30V @ 3.75A	MCTA225/30
	0-55V, 0-55V @ 2.05A	MCTA225/55
500	0-25V, 0-25V @ 10A	MCTA500/25
	0-30V, 0-30V @ 8.33A	MCTA500/30
	0-35V, 0-35V @ 7.14A	MCTA500/35
	0-45V, 0-45V @ 5.56A	MCTA500/45
	0-50V, 0-50V @ 5A	MCTA500/50
	0-55V, 0-55V @ 4.55A	MCTA500/55



Toroidal - Twin Primary Transformers

115V/230V ac



Part Numbers

Load (VA)	Specification	Part Number
625	0-40V, 0-40V @ 7.81A	MCTA625/40
	0-50V, 0-50V @ 6.25A	MCTA625/50
	0-55V, 0-55V @ 5.68A	MCTA625/55
800	0-55V, 0-55V @ 7.27A	MCTA800/55
1000	0-40V, 0-40V @ 12.5A	MCTA1000/40
	0-50V, 0-50V @ 10A	MCTA1000/50
	0-55V, 0-55V @ 9.09A	MCTA1000/55

Toroidal - Twin Primary Transformers

115V/230V ac



Notes:

International Sales Offices:



AUSTRALIA - Farnell InOne
Tel No: ++ 61 2 9645 8888
Fax No: ++ 61 2 9644 7898



FINLAND - Farnell InOne
Tel No: ++ 358 9 560 7780
Fax No: ++ 358 9 345 5411



NETHERLANDS - Farnell InOne
Tel No: ++ 31 30 241 7373
Fax No: ++ 31 30 241 7333



SWITZERLAND - Farnell InOne
Tel No: ++ 41 1 204 64 64
Fax No: ++ 41 1 204 64 54



AUSTRIA - Farnell InOne
Tel No: ++ 43 662 2180 680
Fax No: ++ 43 662 2180 670



FRANCE - Farnell InOne
Tel No: ++ 33 474 68 99 99
Fax No: ++ 33 474 68 99 90



NEW ZEALAND - Farnell InOne
Tel No: ++ 64 9 357 0646
Fax No: ++ 64 9 357 0656



UK - Farnell InOne
Tel No: ++ 44 8701 200 200
Fax No: ++ 44 8701 200 201



BELGIUM - Farnell InOne
Tel No: ++ 32 3 475 2810
Fax No: ++ 32 3 227 3648



GERMANY - Farnell InOne
Tel No: ++ 49 89 61 39 39 39
Fax No: ++ 49 89 613 59 01



NORWAY - Farnell InOne
Tel No: ++ 45 44 53 66 66
Fax No: ++ 45 44 53 66 02



UK - BuckHickman InOne
++ 44 8450 510 150
++ 44 8450 510 130



BRAZIL - Farnell-Newark InOne
Tel No: ++ 55 11 4066 9400
Fax No: ++ 55 11 4066 9410



HONG KONG - Farnell-Newark InOne
Tel No: ++ 852 2268 9888
Fax No: ++ 852 2268 9899



PORTUGAL - Farnell InOne
Tel No: ++ 34 93 475 8804
Fax No: ++ 34 93 474 5288



UK - CPC
++ 44 8701 202 530
++ 44 8701 202 531



CHINA - Farnell-Newark InOne
Tel No: ++86 10 6238 5152
Fax No: ++86 10 6238 5022



IRELAND - Farnell InOne
Tel No: ++ 353 1 830 9277
Fax No: ++ 353 1 830 9016



SINGAPORE - Farnell-Newark InOne
Tel No: ++ 65 6788 0200
Fax No: ++ 65 6788 0300



EXPORT - Farnell InOne
Tel No: ++ 44 8701 200 208
Fax No: ++ 44 8701 200 209

For enquiries from all other markets



DENMARK - Farnell InOne
Tel No: ++ 45 44 53 66 44
Fax No: ++ 45 44 53 66 06



ITALY - Farnell InOne
Tel No: ++ 39 02 93 995 200
Fax No: ++ 39 02 93 995 300



SPAIN - Farnell InOne
Tel No: ++ 34 93 475 8805
Fax No: ++ 34 93 474 5107



ESTONIA - Farnell InOne
Tel No: ++ 358 9 560 7780
Fax No: ++ 358 9 345 5411



MALAYSIA - Farnell-Newark InOne
Tel No: ++ 60 3 7873 8000
Fax No: ++ 60 3 7873 7000



SWEDEN - Farnell InOne
Tel No: ++ 46 8 730 50 00
Fax No: ++ 46 8 83 52 62

<http://www.farnellinone.com>

<http://www.buckhickmaninone.com>

<http://www.cpc.co.uk>

Disclaimer This data sheet and its contents (the "Information") belong to the Premier Farnell Group (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2004.

