


Circuit Protection Terminals

KDKS 1

Warning:

- Install AP partition after last ASK 1 or KDKS 1.
- Disconnect power before replacing the fuse.



Fuse terminals are available with LED blown fuse indicators, which speed identification of fuse failures and reduces costly down time. The maximum operating voltage for the indicator fuse blocks is determined by the LED's rating.

A 2 mA residual current passes through the LED when the fuse is blown, unless otherwise indicated.

	combi-foot	with power on indication	with blown fuse indicator (BFI) and circuit disconnect
Fuse & Feed Through 5 x 20, 5 x 25 mm fuse	Fuse & Feed Through 5 x 20, 5 x 25 mm fuse	Fuse & Feed Through 5 x 20, 5 x 25 mm fuse	Fuse & Feed Through 5 x 20 mm fuse

Note:
In the event of a faulty fuse, the connected circuit has a max. leakage current of .55 mA. With lever open, load is disconnected completely.

Terminal Block Selection Data		Part No.		Part No.		Part No.		Part No.	
Available Options		Version		Part No.		Part No.		Part No.	
Beige PA		9503310000		9503350000					
Beige Wemid		9532440000						7802720000	
24 VDC Hinge -								9908510000	
24 VDC Hinge +						9133151111		9802700000	
6 VDC / 12 VAC						9134521111		9802720000	
12 VDC / 24 VAC						9134531111			
24 VDC / 48 VAC						9134551111		9802760000	
60 VDC / 120 VAC						9134561111		9802780000	
120 VDC / 240 VAC									
Dimensions									
Width / Length / Height mm (in.) for TS 35		8/73.5/55.7 (.31/2.89/2.19)		8/73.5/55.7 (.31/2.89/2.19)		8/73.5/55.7 (.31/2.89/2.19)		8/73.5/55.7 (.31/2.89/2.19)	
Insulation stripping length mm (in.)		9 (.35)		9 (.35)		9 (.35)		9 (.35)	
Technical Data									
Rated voltage / rated current / wire size		UL 300 V / 10/20 A† / #22...12 AWG		300 V / 10/20 A† / #22...12 AWG		300 V / 10/20 A† / #22...12 AWG		300 V / 10/20 A† / #22...12 AWG	
		CSA 300 V / 10/25 A† / #22...12 AWG		300 V / 10/25 A† / #22...12 AWG		300 V / 10/25 A† / #22...12 AWG		300 V / 10/25 A† / #22...12 AWG	
		VDE 500 V / 6.3 A* / 4 mm²		500 V / 6.3 A* / 4 mm²					
Torque Nm (lb. in.)		0.6 (5.5)		0.6 (5.5)		0.6 (5.5)		0.6 (5.5)	
Clamping screw		M 3		3		3		3	
Selected Accessory Data†									
End Plate (AP) (thickness mm)		Type		Part No.		Type		Part No.	
Beige PA		AP KDKS 1 (1.5)		9503330000		AP KDKS 1 (1.5)		9503330000	
Beige Wemid		AP KDKS 1 (1.5)		9532470000					
Jumpers									
2 pole		QB2		0461100000		QB2		0461100000	
3 pole		QB3		0461200000		QB3		0461200000	
4 pole		QB4		0461300000		QB4		0461300000	
G Fuse Cartridges, 5 x 20 mm									
Rated current (A): 0.10 rapid-blow		0430300000		0430300000		0430300000		0430300000	
Rated voltage 250 VAC		0430400000		0430400000		0430400000		0430400000	
Note: For listing of 5 x 25 mm fuses see page 28.		0430500000		0430500000		0430500000		0430500000	
0.25 rapid-blow		0430600000		0430600000		0430600000		0430600000	
0.50 rapid-blow		0430700000		0430700000		0430700000		0430700000	
1.0 rapid-blow		0430900000		0430900000		0430900000		0430900000	
2.0 rapid-blow		0431100000		0431100000		0431100000		0431100000	
3.15 rapid-blow		0431300000		0431300000		0431300000		0431300000	
5.0 rapid-blow									
Disconnect Lever Accessories									
Spare lever		TH		0377060000		TH		0377060000	
Spare lever - BFI 24 VDC H-								9908660000	
Spare lever - BFI 24 VDC H+								9908670000	
Spare lever - BFI 120 VAC/DC								9908680000	
Red pull lever		SIHA		1593020000		SIHA		1593020000	
Brass slug (solid)		SBL		0446100000		SBL		0446100000	
Brass slug (hollow)		SBL		2012750000		SBL		2012750000	
Plastic strip for ganging levers**		Sch S2		0337400000		Sch S2		0337400000	
Tools									
Screwdriver		SD		9008330000		SD		9008330000	
Marking Tags									
Consecutive horizontal		DEK 5/6.5		0468160001		DEK 5/6.5		0468160001	
Consecutive vertical		DEK 5/6.5		0468260001		DEK 5/6.5		0468260001	
Note: Part numbers shown are for a single card of pre-printed tags numbered 1-50.									
For additional information, see Accessories section.									

RAIL MOUNTED TERMINAL BLOCKS: W-SERIES

†See Accessories section for additional information.
 *Rated thermal current to VDE 0611 = 6.3 A, when used for short-circuit fusing up to 15 A (VDE).
 **Provided in one meter strips.
 Note: For 13/32 x 1 1/2 fuses, use SAKS 4 (part no. 0178220000), ratings 600 V / 30 A / #20...8 AWG
 †10 A upper level (fused), 20 A lower level (feed-through) – UL
 †10 A upper level (fused), 25 A lower level (feed-through) – CSA