

DISTRIBUTION AMPLIFIERS

- Allows distribution to multiple TV's around the home
- Cost effective
- 1,2,4,6 + 8 Way versions
- Easy to mount fixings
- F Connectors
- Mains powered
- Boxed



Easy to mount fixings



Part No.	334031	334032	334034	334035
Product	1-Way	2-Way	4-Way	4-Way (1 Input)
No. Inputs	1	1	2	1
No. Outputs	1	2	4	4
Input Frequency Range (MHz)				
• Wideband	47-862	47-862	-	47-862
• VHF	-	-	47-230	-
• UHF	-	-	470-862	-
Output Frequency Range (MHz)	47-862	47-862	47-862	47-862
Typical Gain (dB)				
• Wideband	20	2x17	-	4x10
• VHF	-	-	4x10	-
• UHF	-	-	4x11	-
• Full Output	-	-	-	-
Gain Control (dB)	10	10	-	10
Noise (dB)	4	4	5	4
Output Level (dBuV)*	92	95	83	89
Automatic Line Power (UHF Input)	No	No	12V DC/ 50mA	12V DC/ 50mA
Mains Supply	230Vac, ±10%, 50Hz			

Part No.	334036	334043	334038	334044
Product	6+1 Way	6+1 Way (1 Input)	8+1 Way	8+1 Way (1 Input)
No. Inputs	2	1	2	1
No. Outputs	6+1 Full	6+1 Full	8+1 Full	8+1 Full
Input Frequency Range (MHz)				
• Wideband	-	47-862	-	47-862
• VHF	47-230	-	47-230	-
• UHF	470-862	-	470-862	-
Output Frequency Range (MHz)	47-862	47-862	47-862	47-862
Typical Gain (dB)				
• Wideband	-	6x13	-	8x13
• VHF	6x10	-	8x10	-
• UHF	6x11	-	8x11	-
• Full Output	1x18	1x23	1x18	1x23
Gain Control (dB)	-	10	-	10
Noise (dB)	5	5	6	5
Output Level (dBuV)*	6x83 1x96	6x97 1x102	8x83 1x96	8x97 1x102
Automatic Line Power (UHF Input)	12V DC/ 50mA	12V DC/ 50mA	12V DC/ 50mA	12V DC/ 50mA
Mains Supply	230Vac, ±10%, 50Hz			