



- · 38mm panel-mount trackball provides smooth, responsive and precise cursor control
- Vandal resistant version features a stainless steel retention ring and a coated steel ball (mirror finish) (10J BS EN 60068-2-75: 1997)
- · Robust version features a tough phenolic resin ball (black)
- · Sealed against the ingress of liquids & dust to IP65 when ball is stationary (IP54 when rotating)
- Operating temp: -20°C (dry) to +60°C

- Robust chassis designed to provide secure under-panel fixing for maximum resistance to hard use, abuse and vandalism
- On-board encoder automatically configures to provide either USB or PS2 connectivity
- Two 'click keys' (not supplied) can be connected directly to the on-board encoder
- USB and PS2 cables for connection to host system are available separately



















www.storm-interface.com


# **z**torm


## Panel-mount trackballs for industrial and public environments

These 38mm trackballs provide smooth, accurate and responsive cursor control in wet, dirty or aggressive environments. Each device automatically configures to provide USB or PS2 connectivity. Two selector (click) buttons (not supplied) can be configured to provide either left and right click functions or for both buttons to provide left click functions only. These trackballs can be installed as a flush mounted component in a control panel or equipment housing. Cables enabling connection to either USB or PS2 systems are supplied separately. The trackballs are constructed to ensure maximum resistance to hard use, abuse, and vandalism.









#### **Connector Pinout Details**

Button Connections (P1)	PS2 / USB Output Connections (P3)
0V	D- / Data
Button 1 (left)	D+ / Clock
0V	Test Only
Button 2 (right)	Power +5V
0V	Ground 0V
Button 3 (middle)	Not used
	Connections (P1)  0V  Button 1 (left)  0V  Button 2 (right)  0V

The unit automatically selects either USB or PS/2 protocols on power-up. No re-setting of any DIP switches required.

If both buttons are required to be set as left click then a connection must be made between pins on connector P2 using the jumper device (supplied).

Please note that the TEST input is reserved for factory test only. On no account should a connection be made to this terminal.

The Button inputs are pulled high to 5V within the unit.

Both rising and falling edges of this signal are debounced for 30ms.

The Storm Trackball is designed to work with resident drivers and does not require additional software to be loaded.

#### **Electrical**

Supply Voltage 5.0V dc -10% Switch Debounce 30ms rising/falling Supply Current 15mA maximum

Resolution 150 pulses, 600 counts/revolution

#### Environmental

Operating Temp -20°C (dry) to +60°C IP65 seal when ball stationary

IP54 seal when ball rotating

Humidity 95% Rh max, non-condensing

#### Mechanical

Tracking Force 50g nominal any direction Ball Speed 250 rpm maximum Operational Life 10 million revolutions (min) Mounting Angle within 45° from horizontal

#### Material

Robust Trackball Phenolic Resin Vandal Resistant Trackball Surface Treated Steel PTFE with low friction fill Seal Material Vandal Plate Stainless Steel

NB. Robust Version does not have Vandal Plate

Storm Interface Suite 202 364 Pennsylvania Avenue Glen Ellyn IL 60137 USA

Tel: (630) 469 2981 Fax: (630) 469 2975 Email: sales.usa@storm-keypads.com

UK Office:

Storm Interface 14 Bentinck Court Bentinck Road West Drayton Middlesex UB7 7RQ

Tel: +44 (0)1895 431421 Fax: +44 (0)1895 431132 Email: sales@storm-interface.com

#### www.storm-interface.com

Storm is a trademark of Keymat Technology Ltd ace is a trading name of Keymat Technology Ltd

Storm Interface products include technology protected by international patents and design registration. All rights reserved.

#### Installation

Prepare plate with hole for ø43.0mm bezel and M3 x 40mm studs on 52.5mm centres. Fit sealing gasket to trackball.

Place trackball over studs.

Place vandal plate over studs (VR version only).

Secure with plain washers and Nyloc nuts.

IMPORTANT: Max torque 40Ncm on nuts.

Connect switches to connector P1

If reqd,fit jumper to enable both buttons as left click.

### Accessories [x] denotes packaging variant

Stock No.

2200-00200[x] Cable 2.5m PS2 2200-00300[x] Cable 2.5m USB

2200-00020[x] Trackball Unit PS2 / USB Black Phenolic Ball 2200-00030[x] Trackball Unit PS2 / USB Coated Steel Ball

Whilst every effort is made to ensure details are correct at time of print, specifications are subject to change without notice



2200-LIT-01 Rev 2 +44 (0)7810 551046 Oct 2004



FM 39602