



PART NO.


MC3811-091 Series

		REVISIONS						
ECN #	REV	DESCRIPTION	DRAWN	DATE	CHECKD	DATE	APPRVD	DATE
-	Α	RELEASED	S. R	17/3/06	K. S	17/3/06	N. K	31/3/06

Miniature







Dimensions: Millimetres

Feature:

• Miniature illuminated rocker switches which fit standard panel cut-out.

Specifications:

: CSA Rating - 16A 125V ac.

- 8A 250V ac.

VDE - 10(6)A 250V ac. **SEMKO** - 10(6)A 250V ac.

Contact Resistance : $20m\Omega$. Insulation Resistance : >50M Ω .

Dielectric Strength : Up to 3.5kV ac. Mechanical Endurance : >100,000 cycles.

Circuit : DPST.

Recommended Panel Cut-Out : Thickness (mm) Cut-out size (mm).

> 1.0 (minimum) 19.3 x 13.0. 3.0 (maximum) 19.5 x 13.0.

Terminal : 4.8mm Quick Connect

PC Tail/Angle PC Tail,

Solder Tail.

Operating Temperature : 0°C to +85°C.

Inrush Current : 100A.

Specification Table

Туре	Colour	Bezel	Depth	Tabs	Part Number
Illuminated	Red	21 x 15	22.2	4.8 x 0.8	MC3811-091-02
illullillateu	Green	21 X 10		4.0 % 0.0	MC3811-091-05

Dimensions: Millimetres

Α

This data sheet and its contents (the "Information") belong to the Premier Farnell Group (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. MULTICOMP is the registered trademark of the Group. @ Premier Farnell plc 2004.

TOLERANCES:

UNLESS OTHERWISE SPECIFIED, **DIMENSIONS ARE** FOR REFERENCE PURPOSES ONLY.

DRAWN BY:	DATE:
S. Ram	17/03/06
CHECKED BY:	DATE:
K. Suresh	17/03/06
APPROVED BY:	DATE:
N. Kiwomya	31/03/06

DRAWING TITLE:

MC-3811-091 Series - Rocker Switches

DWG NO. SIZE M10000230 **ELECTRONIC FILE** REV 213292 2 DWG

SCALE: NTS U.O.M.: mm SHEET: 1 OF 2



PART NO.

MC3811-091 Series

REVISIONS				·	·	·		·
ECN #	REV	DESCRIPTION	DRAWN	DATE	CHECKD	DATE	APPRVD	DATE
-	Α	RELEASED	S. R	17/3/06	K. S	17/3/06	N. K	31/3/06

Notes:

International Sales Offices:

AUSTRALIA - Farnell InOne

Tel No: ++ 61 2 9645 8888

Fax No: ++ 61 2 9644 7898

AUSTRIA - Farnell InOne

Tel No: ++ 43 662 2180 680 Fax No: ++ 43 662 2180 670

BELGIUM - Farnell InOne

Tel No: ++ 32 3 475 2810 Fax No: ++ 32 3 227 3648

BRAZIL - Farnell-Newark InOne

Tel No: ++ 55 11 4066 9400 Fax No: ++ 55 11 4066 9410

CHINA - Farnell-Newark InOne

Tel No: ++86 10 6238 5152 Fax No: ++86 10 6238 5022

DENMARK - Farnell InOne Tel No: ++ 45 44 53 66 44 Fax No: ++ 45 44 53 66 06

ESTONIA - Farnell InOne

Tel No: ++ 358 9 560 7780 Fax No: ++ 358 9 345 5411

FINLAND - Farnell InOne Tel No: ++ 358 9 560 7780 Fax No: ++ 358 9 345 5411

FRANCE - Farnell InOne

Tel No: ++ 33 474 68 99 99 Fax No: ++ 33 474 68 99 90 **GERMANY** - Farnell InOne

Tel No: ++ 49 89 61 39 39 39 Fax No: ++ 49 89 613 59 01

SINGAPORE -

Farnell-Newark InOne

Tel No: ++ 65 6788 0200

Fax No: ++ 65 6788 0300

Tel No: ++ 34 93 475 8805

Fax No: ++ 34 93 474 5107

SWEDEN - Farnell InOne

Tel No: ++ 46 8 730 50 00

Fax No: ++ 46 8 83 52 62

SWITZERLAND - Farnell InOne

Tel No: ++ 41 1 204 64 64 Fax No: ++ 41 1 204 64 54

Tel No: ++ 44 8701 200 200

Fax No: ++ 44 8701 200 201

UK - BuckHickman InOne

UK - Farnell InOne

++ 44 8450 510 150

++ 44 8450 510 130

++ 44 8701 202 530

++ 44 8701 202 531

UK-CPC

SPAIN - Farnell InOne

HONG KONG -Farnell-Newark InOne

Tel No: ++ 852 2268 9888 Fax No: ++ 852 2268 9899

IRELAND - Farnell InOne

Tel No: ++ 353 1 830 9277 Fax No: ++ 353 1 830 9016

ITALY - Farnell InOne

Tel No: ++ 39 02 93 995 200 Fax No: ++ 39 02 93 995 300

MALAYSIA -Farnell-Newark InOne

Tel No: ++ 60 3 7873 8000 Fax No: ++ 60 3 7873 7000

NETHERLANDS - Farnell InOne

Tel No: ++ 31 30 241 7373 Fax No: ++ 31 30 241 7333

NEW ZEALAND - Farnell InOne

Tel No: ++ 64 9 357 0646 Fax No: ++ 64 9 357 0656

NORWAY - Farnell InOne

Tel No: ++ 45 44 53 66 66 Fax No: ++ 45 44 53 66 02

PORTUGAL - Farnell InOne

Tel No: ++ 34 93 475 8804 Fax No: ++ 34 93 474 5288

EXPORT - Farnell InOne Tel No: ++ 44 8701 200 208 Fax No: ++ 44 8701 200 209

For enquiries from all other markets

http://www.farnellinone.com

http://www.buckhickmaninone.com

http://www.cpc.co.uk

This data sheet and its contents (the "Information") belong to the Premier Farnell Group (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change with out notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence.

MULTICOMP is the registered trademark of the Group. © Premier Farnell plc 2004.

UNLESS OTHERWISE SPECIFIED, **DIMENSIONS ARE** FOR REFERENCE

PURPOSES ONLY.

TOLERANCES:

DRAWN BY:	DATE:
S. Ram	17/03/06
CHECKED BY:	DATE:
K. Suresh	17/03/06
APPROVED BY:	DATE:
N. Kiwomya	31/03/06

DRAWING TITLE:

MC-3811-091 Series - Rocker Switches

SIZE DWG NO.

M10000230

ELECTRONIC FILE 213292 2 DWG

SHEET: 2 OF 2

SCALE: NTS U.O.M.: mm

REV

Α