Honeywell

FR/SR Series

Full Sized, Sealed Rocker Switches

DESCRIPTION FR SERIES

The FR Series illuminated and non-illuminated full size sealed rocker switches offer enhanced design flexibility and set new standards for both performance and reliability. The switches are designed to fit industry standard mounting holes of 44,0 mm x 22,0 mm (1.734 in x 0.867 in) and offer a variety of switch and lamp circuit combinations.

FEATURES FR SERIES

- Expected electrical life 50,000 cycles momentary; 100,000 cycles maintained
- Expected mechanical life 250,000 cycles minimum
- Sealed to IP67
- One or two pole circuitry options
- Withstands operating temperatures from -40 °C to 85 °C (-40 °F to 185 °F)
- Welded lamp connection and one-piece internal, jumperless terminal withstand extreme shock and vibration
- 12 terminals offer an extensive range of switch and lamp circuit options, including LED or incandescent illumination.
- · Vibration and shock resistant

POTENTIAL APPLICATIONS FR/SR SERIES

- Transportation industry
- Test equipment
- · Heavy duty machinery
- Marine equipment

FR SERIES





SR SERIES

The SR Series illuminated and non-illuminated full size sealed rocker switches offer robust performance in a flexible package. These switches are available in single or double pole configurations, have an optional panel seal and the SRL Series can be illuminated with square or bar shaped lenses.

SR SERIES

- Expected electrical life 50,000 cycles momentary;
 100,000 cycles maintained
- Expected mechanical life 150,000 cycles minimum
- Dual switch seal certified to IP66/IP68.
- UL recognised, CSA certified
- Optional panel seal prevents water/dust ingress behind panel
- Offered in both 8 and 10 terminal base options. AMP and Packard compatible connectors available.
- Withstands operating temperatures from -40 °C to 85 °C (-40 °F to 185 °F)
- Optional rocker boot available for non-illuminated SRN Series

FRN Series


Sealed Rocker Switches, Non-illuminated

OPERATING CHARACTERISTICS


OI ENATING CHARACTERISTICS			
Electrical life		50,000 cycles momentary;	
		100,000 cycles maintained	
Mechanical life		250,000 cycles min.	
Operating temper	erature	-40 °C to 85 °C (-40 °F to 185 °F)	
	Type 91	0.250 in x 0.032 in	
		[6,35 mm x 0,81 mm] wide tab (QC)	
Termination/		20 A, 12 V	
Electrical rating	Type 93	0.187 in x 0.032 in	
		[4,75 mm x 0,81 mm] wide tab (QC)	
		15 A, 12 V	
Vibration		Per Mil-Std-202F, Method 204D	
		Test Condition A, 10 G, 10-500 Hz	
Shock		Per Mil-Std-202F, Method 213B	
		Test Condition K, 30 G	
Thermal Shock		Per Mil-Std-202F, Method 107F	
		Test Condition A, -55 °C to 85 °C	
Salt Spray		Per Mil-Std-202F, Method 101D	
		Test Condition A, 48 Hr	
Moisture Resistance		Per Mil-Std-202F, Method 106F	
		Test Criteria: pre and post test	
		contact resistance	
Sealing		IP67	



PART NUMBER TREE



MOUNTING DRAWINGS, FOR REFERENCE ONLY (IN [MM])



NOTE

Not all permutations
are available. Contact
Honeywell for more
information.

		CIRCUIT MADE WITH ROCKER IN		
		POSITION 3 (182, 586)	POSITION 2	POSITION 1 (284, 688)
	ı	ON	OFF	ON
	?	OFF	NONE	ON
[;	3	ON	NONE	ON
	1	(OFF)	NONE	ON
	5	(ON)	OFF	ON
	;	OFF	NONE	(ON)
	1	(ON)	OFF	(ON)
	3	(ON)	NONE	ON

Note: () denotes momentary action

ORDER GUIDE

Description	Listing
Non-illuminated	FRN91-12BB
Non-illuminated	FRN91-22BB
Non-illuminated	FRN91-16BB
Non-illuminated	FRN91-26BB
Non-illuminated	FRN91-14BB
Non-illuminated	FRN91-24BB
Non-illuminated	FRN91-13BB
Non-illuminated	FRN91-23BB
Non-illuminated	FRN91-18BB
Non-illuminated	FRN91-28BB
Non-illuminated	FRN91-11BB
Non-illuminated	FRN91-21BB
Non-illuminated	FRN91-15BB
Non-illuminated	FRN91-25BB
Non-illuminated	FRN91-17BB
Non-illuminated	FRN91-27BB
Connector Housing	FR-01


FRL Series

Sealed Rocker Switches, Illuminated

OPERATING CHARACTERISTICS


OF ENATING CHARACTERISTICS			
Electrical life		50,000 cycles momentary;	
		100,000 cycles maintained	
Mechanical life		250,000 cycles min	
Operating temperating	erature	-40 °C to 85 °C (-40 °F to 185 °F)	
	Type 91	0.250 in x 0.032 in	
		[6,35 mm x 0,81 mm] wide tab (QC)	
Termination/		20 A, 12 V	
Electrical rating	Type 93	0.187 in x 0.032 in	
		[4,75 mm x 0,81 mm] wide tab (QC)	
		15 A, 12 V	
Vibration		Per Mil-Std-202F, Method 204D	
		Test Condition A, 10 G, 10-500 Hz	
Shock		Per Mil-Std-202F, Method 213B	
		Test Condition K, 30 G	
Thermal Shock		Per Mil-Std-202F, Method 107F	
		Test Condition A, -55 °C to 85 °C	
Salt Spray		Per Mil-Std-202F, Method 101D	
		Test Condition A, 48 Hr	
Moisture Resista	ince	Per Mil-Std-202F, Method 106F	
		Test Criteria: pre and post test	
		contact resistance	
Sealing		IP67	
Illuminated LED		Rated 100,000 hours ½ life	
		(LED is internally ballasted for	
		voltages to 24 Vdc)	

MOUNTING DRAWINGS, FOR REFERENCE ONLY (IN [MM])





PART NUMBER TREE



NOTE

2 = 6 V 3 = 12 V

4 = 24 V

Not all permutations are available. Contact Honeywell for more information.

	CIRCUIT MADE WITH ROCKER IN		
	POSITION 3 (182, 586)	POSITION 2	POSITION I (284, 688)
ı	ON	OFF	ON
2	OFF	NONE	ON
3	ON	NONE	ON
4	(OFF)	NONE	ON
5	(ON)	OFF	ON
6	OFF	NONE	(ON)
7	(ON)	OFF	(ON)
8	(ON)	NONE	ON

Note: () denotes momentary action

ORDER GUIDE

Description	Listing
Illuminated	FRL91-22CGA3-BB79
Illuminated	FRL91-23CGA3-BB79
Illuminated	FRL91-21CGG3-BB77
Illuminated	FRL91-27CGG3-BB77
Connector Housing	FR-01


SRN Series

Sealed Rocker Switches, Non-illuminated

OPERATING CHARACTERISTICS


OPERATING CHARACTERISTICS		
50,000 cycles momentary;		
100,000 cycles maintained		
150,000 cycles min.		
-40 °C to 85 °C (-40 °F to 185 °F)		
0.250 in x 0.032 in		
[6,35 mm x 0,81 mm] wide tab (QC)		
10 A 250 Vac ½ HP / UL, CSA		
15 A 125 Vac ½ HP / UL, CSA		
Per Mil-Std-202F, Method 204D		
Test Condition A, 10 G, 10-500 Hz		
Per Mil-Std-202F, Method 213B		
Test Condition K, 30 G		
Per Mil-Std-202F, Method 107F		
Test Condition A, -55 °C to 85 °C		
Per Mil-Std-202F, Method 101D		
Test Condition A, 48 Hr		
Per Mil-Std-202F, Method 106F		
Test Criteria: pre and post test		
contact resistance		
IP66/IP68		
All switches with a sealed		
construction meet the require-		
ments of UL1500/ISO8846 for		
ignition protection, in addition to		
conformance with EC directive		
94/25/EC for marine products.		

MOUNTING DRAWINGS, FOR REFERENCE ONLY (IN [MM])





PART NUMBER TREE



NOTE

Not all permutations
are available. Contact
Honeywell for more
information.

	CIRCUIT MADE WITH ROCKER IN		
	POSITION 3 (182, 485)	POSITION 2	POSITION 1 (283, 586)
ı	ON	OFF	ON
2	OFF	NONE	ON
3	ON	NONE	ON
4	(OFF)	NONE	ON
5	(ON)	OFF	ON
6	OFF	NONE	(ON)
7	(ON)	OFF	(ON)
8	(ON)	NONE	ON

Note: () denotes momentary action

ORDER GUIDE

Description	Listing	
Non-illuminated	SRN91-12BB	
Non-illuminated	SRN91-22BB	
Non-illuminated	SRN91-16BB	
Non-illuminated	SRN91-26BB	
Non-illuminated	SRN91-14BB	
Non-illuminated	SRN91-24BB	
Non-illuminated	SRN91-13BB	
Non-illuminated	SRN91-23BB	
Non-illuminated	SRN91-18BB	
Non-illuminated	SRN91-28BB	
Non-illuminated	SRN91-11BB	
Non-illuminated	SRN91-21BB	
Non-illuminated	SRN91-15BB	
Non-illuminated	SRN91-25BB	
Non-illuminated	SRN91-17BB	
Non-illuminated	SRN91-27BB	
Connector Housing	HRSR-01	
Rocker Boot	SR-01	


SRL Series

Sealed Rocker Switches, Illuminated

OPERATING CHARACTERISTICS


OI EIIAIING OIIAIIAOI	LINGTIOS	
Electrical life	50,000 cycles momentary; 100,000	
	cycles maintained	
Mechanical life	150,000 cycles min.	
Operating temperature	-40 °C to 85 °C (-40 °F to 185 °F)	
Termination	0.250 in x 0.032 in	
	[6,35 mm x 0,81 mm] wide tab (QC)	
Electrical rating/Approvals	10 A 250 Vac 1/2 HP / UL, CSA	
	15 A 125 Vac 1/2 HP / UL, CSA	
Vibration	Per Mil-Std-202F, Method 204D	
	Test Condition A, 10 G, 10-500 Hz	
Shock	Per Mil-Std-202F, Method 213B	
	Test Condition K, 30 G	
Thermal Shock	Per Mil-Std-202F, Method 107F	
	Test Condition A, -55 °C to 85 °C	
Salt Spray	Per Mil-Std-202F, Method 101D	
	Test Condition A, 48 Hr	
Moisture Resistance	Per Mil-Std-202F, Method 106F	
	Test Criteria: pre and post test	
	contact resistance	
Sealing	IP66/IP68	
Iluminated:	LED Rated 100,000 hours ½ life	
	(LED is internally ballasted for	
	voltages to 24 Vdc)	
Ignition protection	All switches with a sealed	
	construction meet the require	
	ments of UL1500/ISO8846 for	
	ignition protection, in addition to	
	conformance with EC directive	
	94/25/EC for marine products.	

MOUNTING DRAWINGS, FOR REFERENCE ONLY (IN [MM])





PART NUMBER TREE



	CIRCUIT MADE WITH ROCKER IN		
	POSITION 3 (182, 485)	POSITION 2	POSITION (283, 586)
ı	ON	OFF	ON
2	OFF	NONE	ON
3	ON	NONE	ON
4	(OFF)	NONE	ON
5	(ON)	OFF	ON
6	OFF	NONE	(ON)
7	(ON)	OFF	(ON)
R	(ON)	NONE	ON

Note: () denotes momentary action

information.

NOTE

Not all permutations

are available. Contact Honeywell for more

ILLUMINATION CIRCUIT DIAGRAMS

ORDER GUIDE

LED voltage

2 = 6 V 3 = 12 V

4 = 24 V

ONDEN GOIDE		
Description	Listing	
Illuminated	SRL91-22ARN3-BB9N	
Illuminated	SRL91-23URR3-BB99	
Illuminated	SRL91-21URR3-BB99	
Illuminated	SRL91-27URR3-BB99	
Illuminated	SRL91-22UGA3-BB99	
Illuminated	SRL91-23UGG3-BB99	
Illuminated	SRL91-21UGG3-BB99	
Illuminated	SRL91-22UGG3-BB99	
Connector Housing	HRSR-01	

WARNING MISUSE OF DOCUMENTATION

- The information presented in this product sheet is for reference only.
 Do not use this document as a product installation guide.
- Complete installation, operation, and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in death or serious injury.

WARNING PERSONAL INJURY

DO NOT USE these products as safety or emergency stop devices or in any other application where failure of the product could result in personal injury. Failure to comply with these instructions could result in death or serious injury.

WARRANTY/REMEDY

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Honeywell's standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items it finds defective. The foregoing is buyer's sole remedy and

foregoing is buyer's sole remedy and is in lieu of all warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.

While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.

Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

SALES AND SERVICE

Honeywell serves its customers through a worldwide network of sales offices, representatives and distributors. For application assistance, current specifications, pricing or name of the nearest Authorized Distributor, contact your local sales office or:

E-mail: info.sc@honeywell.com

Internet: www.honeywell.com/sensing

Phone and Fax:

Asia Pacific +65 6355-2828

+65 6445-3033 Fax

Europe +44 (0) 1698 481481

+44 (0) 1698 481676 Fax

Latin America +1-305-805-8188

+1-305-883-8257 Fax

USA/Canada +1-800-537-6945

+1-815-235-6847

+1-815-235-6545 Fax

Automation and Control Solutions

Sensing and Control Honeywell 1985 Douglas Drive North Golden Valley, MN 55422 www.honeywell.com/sensing

