



**Product Details: Tenma 72-7224  
Compact Clamp Meter w/Frequency**

Perfect for general purpose applications, this compact clamp meter measures AC/DC voltage, AC/DC current, resistance, frequency and duty cycle. **Features:**

- 3999 count autoranging display
- 10M $\Omega$  input impedance
- 1" clamp diameter
- Relative mode
- Diode test
- Continuity buzzer
- Data hold
- Full icon display
- Sleep mode
- Low battery indicator
- Includes zipper case, test leads, owners manual
- Requires one 9V battery (292-035), included

<b>Specifications</b>	<b>Range</b>	<b>Accuracy</b>
DC voltage	400mV, 4V, 40V, 400V, 600V	$\pm(0.8\% +1)$
AC voltage	4V, 40V, 400V, 600V	$\pm(1\% +5)$ .
DC current	40A, 400A	$\pm(2\% +3)$
AC current	40A, 400A	$\pm(2.5\% +5)$
Resistance	400 $\Omega$ , 4K $\Omega$ , 40K $\Omega$ , 400K $\Omega$ , 4M $\Omega$ , 40M $\Omega$	$\pm(1\% +2)$
Frequency	10Hz ~ 100MHz	$\pm(0.1\% +3)$
Duty Cycle	0.1 ~ 99.9%	