Honeywell



Representative photograph, actual product appearance may varv.

Due to regional agency approval requirements, some products may not be available in your area. Please contact your regional Honeywell office regarding your product of choice.

14CE1-Q

Miniature Enclosed Switches Series 14CE: Top Plunger; 1NC 1NO SPDT Snap Action; 4-Pin DC Micro-Connector

Features

- Compact construction
- Pre-wired or connector versions
- Die-cast Zinc housing
- Wide selection of actuators
- · Gang mounting capability
- Cable length variations
- Side and bottom exit cable/connector
- Simple two-screw mounting
- Low temperature variants
- Fluorocarbon sealing (standard)

Typical Applications

- Processing Equipment
- Textile Machinery
- Machine Tools
- Robotics
- Packaging Equipment
- Farm Machinery
- Commercial Laundry Equipment
- Printing Trade Machinery
- Vehicles

Description

All 14CE and 914CE series miniature enclosed switches incorporate fluorocarbon diaphragm sealing to provide reliable protection, meeting NEMA 1, 2, 3, 3R, 4, 6, 6P, and 13 as well as IP66, IP67, and IP68 requirements. Versions with boot seal also meet NEMA 12 requirements (dust, falling dirt, liquid media with solid contaminates). The cable or connector and basic switch terminals are encapsulated in an epoxy compound, offering superior resistance in harsh environments. For low temperature applications (down to -40 degrees C, -40 degrees F), CE switches can be supplied with low temperature seals and lubricant.

The CE switches are a rugged and versatile switch which can be applied indoors in harsh factory floor applications, as well as on outdoor equipment in extreme temperatures. A full range of actuators are available, including plain plungers, roller plungers, side rotary, multi-directional wire, and manually operated. The switches are also available with the industry standard, M12 miniature 4-pin connector. The 14 CE versions are designed for European applications and meet the requirements of the low voltage directive and therefore carry the CE mark. The 914CE

products meet UL and CSA standards, as well as European CE requirements.

Honeywell

14CE1-Q

Miniature Enclosed Switches Series 14CE: Top Plunger; 1NC 1NO SPDT Snap Action; 4-Pin DC Micro-Connector

| Product Specifications | |
|--------------------------------|---|
| Availability | Europe; Asia-Pacific |
| Product Type | Miniature Limit Switches |
| Actuator | Top Plunger |
| Lever Style | None |
| Circuitry | 1NC 1NO SPDT Snap Action |
| Ampere Rating | 3 A (Thermal) |
| Supply Voltage | 125 Vac, 250 Vac |
| Housing Material | Zinc Die-Cast |
| Termination Type | 4-Pin DC Micro-Connector |
| Series Name | 14CE Series |
| Sealing | IP65, NEMA 1, 3 |
| Approvals | CE Certified |
| CSA File # | LR15775 |
| UL File # | E41859 |
| Mechanical Life | up to 10 million |
| Operating Temperature Range | 0 °C to 70 °C (35 °F to 160 °F) |
| Comment | Bottom Exit Connector |
| Agency Approvals and Standards | IEC947-5-1, EN60947-5-1 |
| UNSPSC Code | 302119 |
| UNSPSC Commodity | 302119 Switches and controls and relays |
| Sealed | Industrial |

Honeywell

14CE1-Q

Miniature Enclosed Switches Series 14CE: Top Plunger; 1NC 1NO SPDT Snap Action; 4-Pin DC Micro-Connector

A WARNING

IF USED IN APPLICATIONS CONCERNING HUMAN SAFETY

- Only use NC direct opening ("positive opening"/"positive break") contacts,
 - identified by the symbol
- Do NOT use flexible/adjustable actuators. Only use actuators designed for safety applications
- Do NOT defeat, tamper, remove, or bypass this switch.
- Hazardous voltage, disconnect power before servicing.
- Strictly adhere to all installation and maintenance instructions.
- Consult with local safety agencies and their requirements when designing a machine-control link, interface and all control elements that affect safety

Failure to comply with these instructions could result in death or serious injury.

A WARNING

MISUSE OF DOCUMENTATION

- The information presented in this product sheet (or catalog) is for reference only. DO NOT USE this document as product installation information.
- Complete installation, operation and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in death or serious injury.

© Copyright Honeywell Inc.1998-2006 All rights reserved.