

## TW141 1200 to 1750 MHz 40 dB Inline Amplifier

The TW141 by Tallysman Wireless is a rugged, waterproof wideband 40dB gain inline amplifier, specially designed to boost weak frequency signals from 1200 to 1750 MHz, including L-Band and all GNSS (GPS, GLONASS and Galileo) signals. The TW141 provides for much longer cable runs from antenna to receiver without degradation of system sensitivity, for applications such as mast-mount, large vehicle and timing systems.

The TW141 passes DC directly from input to output to support centre conductor DC supply to the antenna, and so avoids the need for an additional bias source or bias "T". It is enclosed in a robust weatherproof cylindrical nickel-plated brass housing (IP67 compliant) and is available with SMA and TNC female connectors.



TW141 Dimensions (mm)





## **Applications**

- Commercial and Military L-Band Satellite Systems
- Wireless Telecom & Cellular Base Station Timing Applications
- GNSS (GPS, GLONASS, Galileo), SBAS and Telematics Systems
- Commercial and Industrial Timing and Synchronization Applications

#### **Features**

- Very low noise: <2dB
- 75 mA max. current consumption
- Wide input voltage 5 to 10 Volts
- Cylindrical nickel-plated brass housing: IP67
- Powered via antenna coax from receiver
- 50 Ohm port impedance
- Available SMA & TNC jack connectors
- RoHS compliant

#### **Benefits**

- Improves signal reception
- Enables extended cable runs
- Avoid installation of costly low-loss cable
- Fits in line with antenna cable
- No external DC power supply required
- Easy to install mounting clamp included



# TW141 1200 to 1750 MHz 40 dB Inline Amplifier

## **Specifications**

#### **Electrical**

Nominal Gain @ 1500 MHz, T=21°C 40 dB + / - 1 dB typ.

**Gain Flatness** ±2 dB **Impedance** 50 Ohms Noise Figure <2 dB

Operational Bandwidth 1200 to 1750 MHz

VSWR 1150 to 1750 MHz ≤2 max. Input Return Loss Zo=50 > -10 dB Output Return Loss Zo=50 > -15 dB Reverse Isolation >35 dB

Output 1dB Compression Level +10 dB **Output IP3** +20 dBm

Supply Range voltage 5 to 10 VDC nominal

**Supply Current** 75 mA max.

#### **Mechanicals & Environmental**

Mechanical Size (body dimensions only) 59 mm L x 20 mm Dia. (2.32" L x 0.787" Dia.)

SMA jack or TNC Jack Connectors

-40 to +85 °C Operating Temp. Range Enclosure Nickel-plated brass

Environmental RoHS and IP67 compliant Warranty One year - parts and labour

### **Ordering Information**

TW141 40dB gain In-Line Amp with SMA Jack 32-0141-0 TW141 40dB gain In-Line Amp with TNC Jack 32-0141-1

Please contact Tallysman Wireless for additional information

## **Tallysman Wireless Inc**

106 Schneider Road, Unit 3 Ottawa ON K2K 1Y2 Canada Tel 613 591 3131 Fax 613 591 3121

sales@tallysman.com

The information provided herein is intended as a guide only and is subject to change without notice. This document is not to be regarded as a guarantee of performance. Tallysman Wireless Inc. hereby disclaims any or all warranties and liabilities of any kind. © 2010 Tallysman Wireless Inc. All rights reserved.