

**Micro Commercial Components** 



Micro Commercial Components 20736 Marilla Street Chatsworth CA 91311

Phone: (818) 701-4933 Fax: (818) 701-4939

Min

Max

# BC846A THRU BC849C

### Features

- Lead Free Finish/RoHS Compliant ("P" Suffix designates
  - RoHS Compliant. See ordering information) Power Dissipation: 0.225W (T<sub>amb</sub>=25°C)(Note 1)
- Collector Current: 0.1A
- Epoxy meets UL 94 V-0 flammability rating
- Moisure Sensitivity Level 1

## **Maximum Ratings**

Operating temperature : -55°C to +150°C
Storage temperature : -55°C to +150°C

### **DEVICE MARKING**

Symbol

BC846A=1A,46A; BC846B=1B,46B;

BC847A=1E,47A; BC847B=1F,47B; BC847C=1G,47C; BC848A=1J,48A; BC848B=1K,48B: BC848C=1L,48C

Parameter


BC849B=49B; BC849C=49C;


### Electrical Characteristics @ $25^{\circ}$ C Unless Otherwise Specified

OFF CHARAC	OFF CHARACTERISTICS					
$V_{(BR)CBO}$	Collector-Base Breakdown Voltage (I <sub>C</sub> =10µAdc, I <sub>E</sub> =0)			Vdc		
	BC846		80			
	BC847		50			
	BC848, BC849		30			
$V_{(BR)CEO}$	Collector-Emitter Breakdown Voltage			Vdc		
	$(I_C=10\text{mAdc}, I_B=0)$					
	BC846		65			
	BC847		45			
	BC848,BC849		30			
$V_{(BR)EBO}$	Collector-Emitter Breakdown Voltage			Vdc		
	(I <sub>E</sub> =10μAdc, I <sub>C</sub> =0)		6			
I <sub>CBO</sub>	Collector Cut-off Current		0.1	μAdc		
	BC846 (V <sub>CB</sub> =80V, I <sub>E</sub> =0)					
	BC847 (V <sub>CB</sub> =50V, I <sub>E</sub> =0)					
<b>—</b>	BC848, BC849 (V <sub>CB</sub> =30V, I <sub>E</sub> =0)		0.1	۸ -۱ -		
I <sub>CEO</sub>	Collector Cut-off Current		0.1	μAdc		
	BC846 ( $V_{CE}$ =60V, $I_{B}$ =0) BC847 ( $V_{CF}$ =45V, $I_{B}$ =0)					
	BC848, BC849 (V <sub>CE</sub> =30V, I <sub>B</sub> =0)					
I <sub>EBO</sub>	Emitter Cut-off Current		0.1	µAdc		
'EBO	(V <sub>EB</sub> =5V, I <sub>C</sub> =0mA)		0.1	μλασ		
H <sub>FE(1)</sub>	DC Current Gain(V <sub>CE</sub> =5V, I <sub>C</sub> =2mA)					
· •FE(1)	BC846A, 847A, 848A	110	220			
	BC846B, 847B, 848B,849B	200	450			
	BC847C, BC848C ,BC849C	420	800			
V <sub>CE(sat)</sub>	Collector-Emitter Saturation Voltage		0.5	Vdc		
()	(I <sub>C</sub> =100mA, I <sub>B</sub> =5mA)					
V <sub>BE(sat)</sub>	Base-Emitter Saturation Voltage		1.1	Vdc		
(/	(I <sub>C</sub> =100mA, I <sub>B</sub> =5mA)					
f⊤	Transition Frequency	100		MHz		
	(V <sub>CE</sub> =5V, I <sub>C</sub> =10mA, f=100MHz)					

### Note 1: Transistor mounted on an FR4 printed-circuit board

# NPN Plastic-Encapsulate Transistors





# 



### **Micro Commercial Components**

### **Ordering Information:**

Device	Packing
Part Number-TP	Tape&Reel 3Kpcs/Reel

### \*\*\*IMPORTANT NOTICE\*\*\*

**Micro Commercial Components Corp.** reserves the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes. **Micro Commercial Components Corp.** does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold **Micro Commercial Components Corp.** and all the companies whose products are represented on our website, harmless against all damages.

### \*\*\*LIFE SUPPORT\*\*\*

MCC's products are not authorized for use as critical components in life support devices or systems without the express written approval of Micro Commercial Components Corporation.

### \*\*\*CUSTOMER AWARENESS\*\*\*

Counterfeiting of semiconductor parts is a growing problem in the industry. Micro Commercial Components (MCC) is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. MCC strongly encourages customers to purchase MCC parts either directly from MCC or from Authorized MCC Distributors who are listed by country on our web page cited below. Products customers buy either from MCC directly or from Authorized MCC Distributors are genuine parts, have full traceability, meet MCC's quality standards for handling and storage. MCC will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. MCC is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.