Automotive Relays





Coil Data

Nominal Voltage Coil Resistance Operate Voltage Release Voltage Coil Power

Contact Data

| Contact Form | : C-1 form C |
|---------------------------|-------------------------------------|
| Contact Material | : Ag Alloy |
| Contact Rating | : 20 A 14 V dc Resistive |
| Maximum Switching Voltage | : 16 V dc |
| Maximum Carrying Current | : 35 A / 10 minutes. 25 A / 1hr |
| Maximum Switching Load | : 35 A |
| Maximum Inrush Current | : 60 A |
| Minimum Switching Load | : 6 V dc 1 A |
| Contact Resistance | : \leq 50 m Ω (6 V dc 1 A) |
| | |

: 12 V dc

: Refer to coil data chart

: Refer to coil data chart : Refer to coil data chart

: 600 mW, 800 mW

Life

| Electrical | : 100,000 operations |
|------------|-------------------------|
| Mechanical | : 10,000,000 operations |

General Data

| Minimum Insulation Resistance | : 100 MΩ 500 V dc |
|-------------------------------|---|
| Dielectric Strength | : 500 V ac, 1 min between open contacts |
| | : 500 V ac, 1 min between coil and contacts |
| Maximum Operate Time | : 10 ms |
| Maximum Release Time | : 10 ms |
| Operate Temperature | : -30 to +85°C |
| | |

Shock Resistance

| Minimum Endurance | : 100 m/s ² |
|----------------------|--------------------------|
| Minimum Misoperation | : 1,000 m/s ² |



Automotive Relays



General Data


Vibration Resistance

Endurance Misoperation Weigh


- : 10 -55 Hz, double amplitude 1.5 mm
- : 10 -55 Hz, double amplitude 1.5 mm
- : Approximately 6 g

13.7

Dimensions




Wiring Diagrams



Mounting Hole Layout

12



Dimensions : Millimetres

Coil Data Chart 20°C

| Nominal Voltage | Coil Resistance | Operate Voltage | Release Voltage | Coil Power |
|-----------------|-----------------|-----------------|-----------------|------------|
| V dc | Ω ±10% | ≤ V dc | ≥V dc | mW |
| 12 | 180 | 7.2 | 1.2 | 800 |


www.element14.com www.farnell.com www.newark.com



Automotive Relays




Characteristic Data



Part Number Table

| Description | Part Number | |
|-----------------------------------|-------------------|--|
| Relay, Auto, SPDT, 12 V dc, 0.8 W | MCCMA51-S-DC12V-C | |

Part Number Explanation:



Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Famell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2011.



www.element14.com www.farnell.com www.newark.com